

## **Power Divider**

### **GHPD4S-2-18G**

#### **Applications**

- . **Wireless Communications**
- . **Military Communications**
- . **SATCOM**
- . **Commercial Communications**
- . **Test and Measurement**

#### **Description**

**GHPD4S-2-18G** 4 way SMA power divider (also known as a SMA coaxial power splitter) is rated for a minimum frequency of 2 GHz and a maximum frequency of 18 GHz. This Goghel 4 port SMA power divider / coaxial splitter has a 50 Ohm impedance and a maximum input power of 20 Watts(cw). Our SMA coaxial RF splitter / divider has a female SMA type input and 4 female SMA output ports.

This 4 way SMA RF power divider from Goghel is a reactive design and has a maximum insertion loss of 0. The maximum input VSWR of this SMA reactive splitter / divider is 1.65:1 and the minimum isolation is 18 dB.

Goghel offers power dividers and combiners that are highly reliable with exceptional specifications offering broadband frequency ranges, high isolation, low insertion loss, low VSWR, low and high power solutions and can utilize different material construction such as stripline, microstrip, and lumped element technology to support various requirements and applications.

## Electrical Specifications

|                           |                        |
|---------------------------|------------------------|
| Model                     | GHPD4S-2-18G           |
| NO.of Ways                | 4                      |
| Frequency Range (GHz)     | 2 ~ 18                 |
| Insertion Loss (dB)       | ≤2.5                   |
| Isolation(dB)             | ≥ 18                   |
| VSWR                      | ≤ 1.65:1               |
| Amplitude Balance(dB)     | ≤ ±0.5                 |
| Phase Balance(° )         | ≤ ±5                   |
| Power Handling(Watt)      | Forward Power:≤20 (CW) |
| Operating Temperature(°C) | -55 ~ +85              |
| Impedance                 | 50Ω                    |
| Port Connectors           | SMA-Female             |
| Surface Color             | Black Paint (Options)  |
| Outline Drawing           | As Below               |

